

Crestron 社の機器およびソフトウェアのコマンドに関しては、下記のものに対応しています。

| Category          | Name                        | Join Type | Join Numbers |        |                |        |
|-------------------|-----------------------------|-----------|--------------|--------|----------------|--------|
|                   |                             |           | RoomView     |        | Control System |        |
| General Info      | Online                      | Digital   | 1            | In     | 1              | In     |
|                   | Help Request                | Serial    | 1            | In/Out | 1              | In/Out |
|                   | Device ID string            | Serial    | 40           | In     | 40             | In     |
| Power             | Power On                    | Digital   | 5            | In/Out | 5              | In/Out |
|                   | Power Off                   | Digital   | 6            | In/Out | 6              | In/Out |
|                   | Status Message              | Serial    | 5001         | In     | 11             | In     |
| Emergency Message | Emergency Alert             | Serial    | 22           | In/Out | 22             | In/Out |
|                   | Emergency Message           | Analog    | 22           | In/Out | 22             | In/Out |
|                   | Emergency Message Supported | Digital   | 22           | In     | 22             | In     |
| Lamp              | Lamp hours Integer          | Analog    | 2            | In     | 2              | In     |
| Picture           | Brightness Level            | Analog    | 5002         | In     | 32             | In     |
|                   | Contrast Level              | Analog    | 5003         | In     | 33             | In     |
|                   | Brightness Plus             | Digital   | 5109         | In/Out | 119            | In/Out |
|                   | Brightness Minus            | Digital   | 5110         | In/Out | 120            | In/Out |
|                   | Contrast Plus               | Digital   | 5111         | In/Out | 121            | In/Out |
|                   | Contrast Minus              | Digital   | 5112         | In/Out | 122            | In/Out |
| Audio             | Volume                      | Analog    | 5012         | In     | 42             | In     |
|                   | Volume Up                   | Digital   | 5115         | In/Out | 125            | In/Out |
|                   | Volume Down                 | Digital   | 5116         | In/Out | 126            | In/Out |
|                   | Mute On                     | Digital   | 5117         | In/Out | 127            | In/Out |
|                   | Mute Off                    | Digital   | 5118         | In/Out | 128            | In/Out |
| Network           | IP Address                  | Serial    | 5040         | In     | 50             | In     |
|                   | Subnet Mask                 | Serial    | 5041         | In     | 51             | In     |
|                   | Default Gateway             | Serial    | 5042         | In     | 52             | In     |
|                   | DNS Server                  | Serial    | 5043         | In     | 53             | In     |
|                   | Mac Address                 | Serial    | 5044         | In     | 54             | In     |
|                   | Control System IP Address   | Serial    | 5045         | In     | 55             | In     |
|                   | Control System IP ID        | Serial    | 5046         | In     | 56             | In     |
|                   | Control System Port         | Serial    | 5047         | In     | 57             | In     |
|                   | DHCP Enable                 | Digital   | 5210         | In     | 220            | In     |
|                   | DHCP Disable                | Digital   | 5211         | In     | 221            | In     |
| Source            | Source Select 1             | Digital   | 5070         | In/Out | 80             | In/Out |
|                   | Source Select 2             | Digital   | 5071         | In/Out | 81             | In/Out |
|                   | Source Select 3             | Digital   | 5072         | In/Out | 82             | In/Out |
|                   | Source Select 4             | Digital   | 5073         | In/Out | 83             | In/Out |
|                   | Source Select 5             | Digital   | 5074         | In/Out | 84             | In/Out |

|                           |                         |         |      |        |     |        |
|---------------------------|-------------------------|---------|------|--------|-----|--------|
|                           | Source Select 6         | Digital | 5075 | In/Out | 85  | In/Out |
|                           | Source Select 7         | Digital | 5076 | In/Out | 86  | In/Out |
|                           | Source Select 8         | Digital | 5077 | In/Out | 87  | In/Out |
|                           | Source Select 9         | Digital | 5078 | In/Out | 88  | In/Out |
|                           | Source Select 11        | Digital | 5080 | In/Out | 90  | In/Out |
|                           | Source Select 12        | Digital | 5081 | In/Out | 91  | In/Out |
|                           | Source Select 13        | Digital | 5082 | In/Out | 92  | In/Out |
|                           | Source Select 14        | Digital | 5083 | In/Out | 93  | In/Out |
|                           | Source 1 Name Text      | Serial  | 5070 | In/Out | 80  | In/Out |
|                           | Source 2 Name Text      | Serial  | 5071 | In/Out | 81  | In/Out |
|                           | Source 3 Name Text      | Serial  | 5072 | In/Out | 82  | In/Out |
|                           | Source 4 Name Text      | Serial  | 5073 | In/Out | 83  | In/Out |
|                           | Source 5 Name Text      | Serial  | 5074 | In/Out | 84  | In/Out |
|                           | Source 6 Name Text      | Serial  | 5075 | In/Out | 85  | In/Out |
|                           | Source 7 Name Text      | Serial  | 5076 | In/Out | 86  | In/Out |
|                           | Source 8 Name Text      | Serial  | 5077 | In/Out | 87  | In/Out |
|                           | Source 9 Name Text      | Serial  | 5078 | In/Out | 88  | In/Out |
|                           | Source 11 Name Text     | Serial  | 5080 | In/Out | 90  | In/Out |
|                           | Source 12 Name Text     | Serial  | 5081 | In/Out | 91  | In/Out |
|                           | Source 13 Name Text     | Serial  | 5082 | In/Out | 92  | In/Out |
|                           | Source 14 Name Text     | Serial  | 5083 | In/Out | 93  | In/Out |
|                           | Current Source          | Serial  | 5010 | In     | 20  | In     |
| <b>Password</b>           | Admin Password Enable   | Digital | 5216 | In/Out | 226 | In/Out |
|                           | Admin Password Disabled | Digital | 5217 | In/Out | 227 | In/Out |
| <b>Info - Advanced</b>    | Projector Name          | Serial  | 5050 | In/Out | 60  | In/Out |
| <b>Picture - Advanced</b> | Freeze On               | Digital | 5105 | In/Out | 115 | In/Out |
|                           | Freeze Off              | Digital | 5106 | In/Out | 116 | In/Out |
|                           | Menu                    | Digital | 5150 | In/Out | 160 | In/Out |
|                           | Up                      | Digital | 5151 | In/Out | 161 | In/Out |
|                           | Down                    | Digital | 5152 | In/Out | 162 | In/Out |
|                           | Left                    | Digital | 5153 | In/Out | 163 | In/Out |
|                           | Right                   | Digital | 5154 | In/Out | 164 | In/Out |
|                           | Exit                    | Digital | 5155 | In/Out | 165 | In/Out |
|                           | Enter                   | Digital | 5156 | In/Out | 166 | In/Out |
|                           | Keystone Plus           | Digital | 5176 | In/Out | 186 | In/Out |
|                           | Keystone Minus          | Digital | 5177 | In/Out | 187 | In/Out |
|                           | AV Mute Off             | Digital | 5190 | In/Out | 200 | In/Out |
|                           | AV Mute On              | Digital | 5191 | In/Out | 201 | In/Out |